

**ECE 732**  
**Advanced Signal Processing**  
**Homework 2**

**FIR Wiener Filtering**

Suppose we observe a signal  $s[n]$  with additive white noise process  $w[n]$  of variance  $\sigma_w^2 = 1$ :

$$x[n] = s[n] + w[n].$$

Let us model the signal as a random process generated by passing another independent white noise process  $v[n]$  of power  $\sigma_v^2$  through a single-pole IIR digital filter:

$$s[n] = \alpha s[n-1] + v[n],$$

where  $0 < \alpha < 1$ .

(a) Give an expression for the autocorrelation function  $R_{ss}[n]$  for the signal  $s[n]$  in terms of  $\sigma_v^2$  and  $\alpha$ .

(b) Design a length-2 FIR Wiener filter to estimate  $s[n]$  from  $x[n]$ . That is, design a length-2 filter  $h[n]$  so that  $\hat{s}[n] = \sum_{k=0}^1 h[k]x[n-k]$  is as close to  $s[n]$  as possible, in the mean-square error sense. Again, express your solution in terms of  $\alpha$  and  $\sigma_v^2$ .

(continued on next page)

**1. (continued)**

(c) Determine the corresponding minimum MSE for this filter (in terms of  $\alpha$  and  $\sigma_v^2$ ).